



YJQ60N03A

N-Channel Enhancement Mode Field Effect Transistor

Product Summary

V_{DS}	30 V
I_D	60 A
$R_{DS(ON)}$ (at $V_{GS}=10V$)	3.2 mohm
$R_{DS(ON)}$ (at $V_{GS}=4.5V$)	4.0 mohm
100% UIS Tested	
100% VDS Tested	

General Description

Trench Power LV MOSFET technology
 Excellent package for heat dissipation
 High density cell design for low $R_{DS(ON)}$

Applications

DC-DC Converters
 Power management functions
 Backlighting

Absolute Maximum Ratings ($T_A=25$ unless otherwise noted)

Parameter		Symbol	Limit	Unit
Drain-source Voltage		V_{DS}	30	V
Gate-source Voltage		V_{GS}	± 20	V
Drain Current	$T_C=25$	I_D	60	A
	$T_C=100$		38	
Pulsed Drain Current ^A		I_{DM}	240	A
Total Power Dissipation @ $T_C=25$ ^B		P_D	75	W
Total Power Dissipation @ $T_C=100$ ^B		P_D	30	W
Total Power Dissipation @ $T_A=25$ ^C		P_D	6.2	W
Single Pulse Avalanche Energy ^D		E_{AS}	400	mJ
Thermal Resistance Junction-to-Case		R_{JC}	1.67	/ W
Thermal Resistance Junction-to-Ambient		R_{JA}	20	/ W
Junction and Storage Temperature Range		T_J, T_{STG}	-55 +150	

Ordering Information (Example)

PREFERRED P/N	PACKING CODE	Marking	MINIMUM PACKAGE(pcs)	INNER BOX QUANTITY(pcs)	OUTER CARTON QUANTITY(pcs)	DELIVERY MODE
---------------	--------------	---------	----------------------	-------------------------	----------------------------	---------------



YJQ60N03A

Electrical Characteristics (T_J=25 unless otherwise noted)

Parameter	Symbol	Conditions	Min	Typ	Max	Units
Static Parameter						
Drain-Source Breakdown Voltage	BV _{DSS}	V _{GS} = 0V, I _D =250μA	30			V
Zero Gate Voltage Drain Current	I _{DSS}	V _{DS} =30V, V _{GS} =0V			1	μA
Gate-Body Leakage Current	I _{GSS}	V _{GS} = 20V, V _{DS} =0V			100	nA
Gate Threshold Voltage	V _{GS(th)}	V _{DS} = V _{GS} , I _D =250μA	1.0	1.5	2.5	V
Static Drain-Source On-Resistance	R _{DS(on)}	V _{GS} = 10V, I _D =20A		2.6	3.2	m
		V _{GS} = 4.5V, I _D =20A		3.4	4.0	
Diode Forward Voltage	V _{SD}	I _S =20A, V _{GS} =0V		0.85	1.2	V
Gate resistance	R _g	F=1 MHz, Open drain		2.9		
Dynamic Parameters						
Input Capacitance	C _{iss}	V _{DS} =15V, V _{GS} =0V, f=1MHZ		4498		pF
Output Capacitance	C _{oss}			800		
Reverse Transfer Capacitance	C _{rss}			643		
Switching Parameters						
Total Gate Charge	Q _g (10V)	V _{GS} =10V, V _{DS} =15V, I _D =20A		92.7		nC
Total Gate Charge	Q _g (4.5V)			46		
Gate-Source Charge	Q _{gs}			13.5		
Gate-Drain Charge	Q _{gd}			22.8		
Reverse Recovery Charge	Q _{rr}	I _F =20A, di/dt=500A/us		3.0		
Reverse Recovery Time	t _{rr}			15		
Turn-on Delay Time	t _{D(on)}	V _{GS} =10V, V _{DD} =20V, I _D =4A, R _L =0.75 R _{GEN} =3		11		ns
Turn-on Rise Time	t _r			80		
Turn-off Delay Time	t _{D(off)}			39		
Turn-off fall Time	t _f			92		

A. Pulse Test: Pulse Width 300us, Duty cycle 2%.

B. The power dissipation P_D is based on T_{J(MAX)}=150, using junction-to-case thermal resistance, and is more useful in setting the upper dissipation limit for cases where additional heatsinking is used.

C. The value of R_{JA} is measured with the device mounted on 1in2 FR-4 board with 2oz. Copper, in a still air environment with TA =25.

D. T_J=25, V_{DD}=20V, V_G=10V, L=2.0mH, I_{AS}=20A.



Typical Performance Characteristics




Figure1. Output Characteristics




Figure2. Transfer Characteristics




Figure3. Capacitance Characteristics




Figure4. Gate Charge




Figure5. Drain-Source on Resistance




Figure6. Drain-Source on Resistance



YJQ60N03A




Figure7. Safe Operation Area




Figure8. Drain current vs. Case Temperature




Figure9. Normalized Maximum Transient Thermal Impedance

DFN3333 Package information



YJQ60N03A

Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website [http:// www.21yangjie.com](http://www.21yangjie.com) , or consult your nearest Yangjie's sales office for further assistance.